

1 EU-TYPE EXAMINATION CERTIFICATE



2 **Equipment or Protective systems intended for use in Potentially
Explosive Atmospheres - Directive 2014/34/EU**

3 **EU-Type Examination Certificate No: FM17ATEX0011X**

4 **Equipment or protective system: Size 1 and 2 CML, CMQ, CMR Series Compact
(Type Reference and Name) Modulating Actuators (CMA)
Electronic Valve Actuators**

5 **Name of Applicant: Rotork Process Controls**

6 **Address of Applicant: 5607 W Douglas Ave
Milwaukee, WI 53218
United States**

7 This equipment or protective system and any acceptable variation thereto is specified in the schedule to this certificate and documents therein referred to.

8 FM Approvals Ltd, notified body number 1725 in accordance with Article 17 of Directive 2014/34/EU of 26 February 2014, certifies that this equipment has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of equipment intended for use in potentially explosive atmospheres given in Annex II to the Directive.

The examination and test results are recorded in confidential report number:

3060693 dated 19th April 2017

9 Compliance with the Essential Health and Safety Requirements, with the exception of those identified in item 15 of the schedule to this certificate, has been assessed by compliance with the following documents:

EN 60079-0:2012 + A11:2013, EN 60079-1:2014, EN 60079-31:2014, EN 13463-1:2009,
EN13463-5:2011, EN 60529:1991 +A1:2000

10 If the sign 'X' is placed after the certificate number, it indicates that the equipment is subject to specific conditions of use specified in the schedule to this certificate.

11 This EU-Type Examination certificate relates only to the design, examination and tests of the specified equipment or protective system in accordance to the directive 2014/34/EU. Further requirements of the Directive apply to the manufacturing process and supply of this equipment or protective system. These are not covered by this certificate.

12 The marking of the equipment or protective system shall include:



II 2 GD c Ex db IIB T4 Gb IP67
Ex tb IIIC T85C Db

For Standard Seals:

Ta = -20°C to +65°C (Standard Version)

Ta = -20°C to +60°C (UPS/HMI and HMI Versions)

For Low Temperature Seals:

Ta = -40°C to +60°C (All Versions)

**Mick Gower
Certification Manager, FM Approvals Ltd.**

Issue date: 09th May 2017

THIS CERTIFICATE MAY ONLY BE REPRODUCED IN ITS ENTIRETY AND WITHOUT CHANGE

FM Approvals Ltd. 1 Windsor Dials, Windsor, Berkshire, UK. SL4 1RS
T: +44 (0) 1753 750 000 F: +44 (0) 1753 868 700 E-mail: atex@fmapprovals.com www.fmapprovals.com

SCHEDULE



Member of the FM Global Group

to EU-Type Examination Certificate No. FM17ATEX0011X

13 Description of Equipment or Protective System:

The CMA (Compact Modulating Actuator) is self contained and used for continuous remote electrical operation of a control valve. The CMA consists of a main flameproof enclosure containing all of the electrical components and an attached smaller mechanical enclosure containing only gearing and mechanical power transfer devices. It is available in three different functions: Linear, Quarter-turn, and Rotary. The main enclosure is defined into "Sizes" per the table below.

The top part of the equipment is the flameproof "d" enclosure (the main enclosure), which is cylindrical in shape and includes a base and cover. The main enclosure is constructed out of the same aluminum either Low Pressure Gravity Cast (LPGC) or High Pressure Die Cast (HPDC). The cover has three different sizes: standard, intermediate and extended. The cover houses a hand-knob which creates a cylindrical flamepath joint with the cover. The user may use the hand-knob to switch from manual to remote operation and control of the actuator. The cover forms a cylindrical flamepath joint with the base to which it is attached by four M8 screws. The joint is provided with suitable seals for environmental protection.

The main enclosure houses all of the electronic components which make up the monitoring and control circuitry. This circuitry consists of power and logic PCBs both mounted on an aluminum bracket. The bracket is fastened to a cast aluminum mount which also acts as a mount for the DC motor. The whole assembly is fastened to the base. The operator uses an LCD display to program the actuator to control the motor and the logic PCB uses a feedback mechanism to sense the position of the output shaft. There are four 3/4 NPT or M25 threaded entries to the enclosure for field wiring purposes.

CML – Linear Compact Modulating Actuator

The mechanical part of the linear enclosure is small in comparison to the main enclosure. This enclosure does not have any electrical components and contains mechanical components only. The enclosure houses a screw shaft which is driven by the DC motor. The shaft is supported by roller bearings and forms a flamepath through the enclosure. The shaft operates with a drive nut to provide the motion to the linear output shaft. The linear output shaft travels through a bronze bushing and into the hazardous area.

This linear output shaft has two shoulder screws threaded into it at an angle perpendicular to the center line of the shaft. The shoulder screws are about 60° apart. One screw is attached to a feedback shaft which penetrates into the electronics enclosure through a bronze bushing creating two flamepaths, one on either side of the bushing. Access to the shoulder screw is via an aluminum plate sealed from the environment. The other shoulder screw is tipped with an arrow to indicate the current position of the actuator to the user. The arrow can be seen through a window which is also sealed from the environment.

The linear actuator is available in a low temperature variant which uses different seals to allow the equipment to be used in the lower minimum ambient temperature of -40°C.

CMQ – Quarter-turn Compact Modulating Actuator

The mechanical part of the quarter turn enclosure is housed in an aluminum lid cast separately from the base of the main enclosure. It is sealed to the base with three screws and an environmental seal. The drive is taken from the motor by the third stage pinion shaft, supported by roller bearings, and into the gear-train. There is a long flamepath along the length of the third stage pinion shaft between the bearings. The gear-train consists of three connected gears which reduce the output RPM and increase the torque. The output shaft is the final shaft passing the drive through the enclosure into the hazardous area through the lid via bronze bushings. The output shaft is connected to a feedback shaft which penetrates into the electronic enclosure through a bronze bushing creating two flamepaths, one on either side of the bushing. Sensors are connected to the feedback shaft to report the position of the actuator to the logic PCB. The final gear is attached to the output shaft and is a half gear with a flat face in order to limit the maximum turning movement of the actuator.

The linear actuator is available in a low temperature variant which uses different seals to allow the equipment to be used in the lower minimum ambient temperature of -40°C.

THIS CERTIFICATE MAY ONLY BE REPRODUCED IN ITS ENTIRETY AND WITHOUT CHANGE

FM Approvals Ltd. 1 Windsor Dials, Windsor, Berkshire, UK. SL4 1RS
T: +44 (0) 1753 750 000 F: +44 (0) 1753 868 700 E-mail: atex@fmapprovals.com www.fmapprovals.com

SCHEDULE



Member of the FM Global Group

to EU-Type Examination Certificate No. FM17ATEX0011X

CMR – Rotary Compact Modulating Actuator

Similar in design to the Quarter-turn, the Rotary variant mechanical side is housed in an aluminum lid cast separately from the base of the main enclosure. It is sealed to the base with three screws and an environmental seal. The drive is taken from the motor by the third stage pinion shaft, supported by roller bearings, and into the gear-train. There is a long flamepath along the length of the third stage pinion shaft between the bearings. The drive is transferred from this shaft onto the fourth stage pinion shaft and finally onto the output shaft which transfers the drive into the hazardous area via a bronze bushing. The output shaft is supported on a single steel roller bearing and also acts as a feedback shaft by passing into the main enclosure, creating a flamepath and allowing sensors to report the actuator position to the logic PCB.

CML-a. Compact Modulating Actuators (CMA).

CMQ-b. Compact Modulating Actuators (CMA).

CMR-c. Compact Modulating Actuators (CMA).

a = Size 100 or 250.

b = Size 250 or 500.

c = Size 50, 100 or 200.

The manufacturer has requested the size 1 and 2 actuators be listed on a separate certificate to the size 3 actuators (see FM17ATEX0012X). The full CMA range includes the following variants:

Model	Size*	Minimum Thrust or Torque	Maximum Thrust or Torque	Speed	Stroke	Shut-off Thrust or Torque
CMR-50	1	2.3 Nm	5.6 Nm	11 RPM	N/A	N/A
CML-100	1	177.9 N	444.8 N	6.35 mm/s	38.1 mm	889.6 N
CMR-100	2	4.5 Nm	11.3 Nm	10 RPM	N/A	N/A
CMR-200	2	9 Nm	22.6 Nm	5 RPM	N/A	N/A
CMQ-250	1	11.3 Nm	28.2 Nm	5 s/qtr-turn	N/A	42.3 Nm
CML-250	2	444.8 N	1112 N	3.175 mm/s	38.1 mm	2200 N
CMQ-500	2	22.6 Nm	56.5 Nm	7.5 s/qtr-turn	N/A	84.8 Nm
CMR-89	3	4.04 Nm	10.1 Nm	24 RPM	N/A	N/A
CMR-125	3	5.6 Nm	14.1 Nm	18 RPM	N/A	N/A
CMR-250	3	11.3 Nm	28.2 Nm	10 RPM	N/A	N/A
CML-750	3	1334.5 N	3336.2 N	3.18 mm/s	50.8 mm	6670 N
CMQ-1000	3	45.2 Nm	113.0 Nm	11 s/qtr-turn	N/A	169.5 Nm

* "Size" refers to performance aspects of the equipment; Sizes 1 and 2 are physically the same.

THIS CERTIFICATE MAY ONLY BE REPRODUCED IN ITS ENTIRETY AND WITHOUT CHANGE

FM Approvals Ltd. 1 Windsor Dials, Windsor, Berkshire, UK. SL4 1RS

T: +44 (0) 1753 750 000 F: +44 (0) 1753 868 700 E-mail: atex@fmapprovals.com www.fmapprovals.com

SCHEDULE



Member of the FM Global Group

to EU-Type Examination Certificate No. FM17ATEX0011X

14 Specific Conditions of Use:

1. The critical dimensions of the flamepath joints are as follows:

CML-100, CML-250 (Size 1 & 2 - Linear)		
Flamepath	Maximum Gap (mm)	Minimum Length L (mm)
Lid/Base	0.15	12.8
Base/Screw Shaft	0.145	13.5
Base/Feedback Shaft Bushing	-0.02	13.7
Feedback Shaft Bushing/Shaft	0.06	13.7
Handknob Shaft/Lid (short cover)	0.10	25.9
Handknob Shaft/Lid (intermediate and extended covers)	0.10	15.7
CMR-50, CMR-100, CMR-200 (Size 1 & 2 - Rotary)		
Flamepath	Maximum Gap (mm)	Minimum Length L (mm)
Lid/Base	0.15	12.8
Base/Pinion Shaft	0.235	29.8
Base/Output Shaft	0.145	12.8
Handknob Shaft/Lid (short cover)	0.10	25.9
Handknob Shaft/Lid (intermediate and extended covers)	0.10	15.7
CMQ-250, CMQ-500 (Size 1 & 2 - Quarter-turn)		
Flamepath	Maximum Gap (mm)	Minimum Length L (mm)
Lid/Base	0.15	12.8
Base/Pinion Shaft	0.235	29.8
Base/Feedback Shaft Bushing	-0.02	13.7
Feedback Shaft Bushing/Shaft	0.06	13.7
Handknob Shaft/Lid (short cover)	0.10	25.9
Handknob Shaft/Lid (intermediate and extended covers)	0.10	15.7

Note that the minimum radial clearance of shafts of rotating electrical machines shall be ≥ 0.05 mm

- Warning - the equipment has a non-metallic coating and has a potential static hazard. Clean only with a damp cloth.
- The screws securing the outer window frame contribute to the integrity of the flameproof enclosure and must not be removed.

15 Essential Health and Safety Requirements:

The relevant EHSRs that have not been addressed by the standards listed in this certificate have been identified and assessed in the confidential report identified in item 8.

16 Test and Assessment Procedure and Conditions:

This EU-Type Examination Certificate is the result of testing of a sample of the product submitted, in accordance with the provisions of the relevant specific standard(s), and assessment of supporting documentation. It does not imply an assessment of the whole production.

Whilst this certificate may be used in support of a manufacturer's claim for CE Marking, FM Approvals Ltd accepts no responsibility for the compliance of the equipment against all applicable Directives in all applications.

This Certificate has been issued in accordance with FM Approvals Ltd's ATEX Certification Scheme.

THIS CERTIFICATE MAY ONLY BE REPRODUCED IN ITS ENTIRETY AND WITHOUT CHANGE

FM Approvals Ltd. 1 Windsor Dials, Windsor, Berkshire, UK. SL4 1RS
T: +44 (0) 1753 750 000 F: +44 (0) 1753 868 700 E-mail: atex@fmapprovals.com www.fmapprovals.com

SCHEDULE



Member of the FM Global Group

to EU-Type Examination Certificate No. FM17ATEX0011X


17 **Schedule Drawings**

A list of the significant parts of the technical documentation is annexed to this certificate and a copy has been kept by the Notified Body.

18 **Certificate History**

Details of the supplements to this certificate are described below:

Date	Description
09 th May 2017	Original Issue.



THIS CERTIFICATE MAY ONLY BE REPRODUCED IN ITS ENTIRETY AND WITHOUT CHANGE

FM Approvals Ltd. 1 Windsor Dials, Windsor, Berkshire, UK. SL4 1RS
T: +44 (0) 1753 750 000 F: +44 (0) 1753 868 700 E-mail: atex@fmapprovals.com www.fmapprovals.com

Blueprint Report

Rotork Process Controls (1000006662)

Class No 3615

Original Project I.D. 3060693

Certificate I.D. FM17ATEX0011X

<u>Drawing No.</u>	<u>Revision Level</u>	<u>Drawing Title</u>	<u>Last Report</u>	<u>Electronic Drawing</u>
046891	G	CMA Approvals for CMA Size 1 & 2 Linear	3060693	Yes (pdf)
047051	G	CMA Approvals for CMA Size 1 & 2 Quarter turn	3060693	Yes (pdf)
047384	G	CMA Approvals for CMA Size 1 & 2 Rotary	3060693	Yes (pdf)
047561	L	Nameplate, CMA, ATEX, IIB, Milwaukee, Size 1 & 2	3060693	Yes (pdf)
047745	C	CMA Approvals Ignition Hazard Assessment for CMA Size 2 Linear	3060693	Yes (pdf)
047746	C	CMA Approvals Ignition Hazard Assessment for CMA Size 2 Rotary	3060693	Yes (pdf)
047747	C	CMA Approvals Ignition Hazard Assessment for CMA Size 2 Quarter Turn	3060693	Yes (pdf)
PUB094-009-00	05/17	CMA Installation and Maintenance Instructions	3060693	Yes (pdf)